9.2-ch Network AV Receiver

VSX-LX504(B)



CUSTOM CONTROL PARTNERS













Control4 and the Control4 logo are registered trademarks of Control4 Corporation. Crestron and the Crestron logo are registered trademark of Crestron Electronics, Inc. AMX and the AMX logo are trademarks of AMX, LLC registered in the U.S. and other countries. Universal Remote Control logo is a registered trademark of Universal Remote Control, Inc. RTI logo is a registered trademark of Remote Technologies Incorporated. Savant Logo is a registered trademark of Savant Systems, LLC.

The Elite VSX-LX504 creates the soundscape of IMAX® Enhanced and Dolby Atmos®/DTS:X ideally calibrated with Advanced MCACC, and even provides similar sound effects with Dolby Atmos Height Virtualizer*¹ without height or surround speakers. Enjoy spectacles from next generation video standards with support for HDCP 2.2, or stream songs across the house with Multi Zone Music, SONOS system, FlareConnect™, Chromecast built-in, DTS Play-Fi®, and Apple AirPlay 2. Other features include Powered Zone 2/Zone 3 Audio, up to 11.2 MHz DSD direct playback, and 2 HDMI outputs.

Amplification

- > Channels: 9
- > Amplification Type: Direct Energy
- > 230 W/ch (6 ohms, 1 kHz, THD 10 %, 1ch Driven)
-) 120 W/ch (8 ohms, 20 Hz-20 kHz, THD 0.08 %, 2ch Driven FTC)

Audio Features

- ➤ IMAX Enhanced*1
- > Dolby Atmos®, Dolby Surround Upmixer supports DTS Formats
- > DTS:X®, DTS Neural:X® Upmixer supports Dolby Formats
- > Reflex Optimizer
- > Dolby Atmos Height Virtualizer*1
- > Dolby® TrueHD, Dolby Digital Plus
- DTS-HD Master Audio, DTS-HD High Resolution Audio, DTS 96/24, DTS-ES, DTS Express
- > DSD Direct Playback via Network/USB (11.2, 5.6, 2.8 MHz/2 ch)
- > DSD Disc (SACD) Playback via HDMI (2.8 MHz/2 ch, 5.1 ch)
- $\textbf{>} \ \, \text{Digital Quad-Core 32-bit DSP (Cirrus Logic) + Aureus} \\ \text{TM floating-point DSP (TI)} \\$
- > 384 kHz/32-bit D/A Conversion with AK4458 (AKM) & PCM5101A (TI)
- > Enhanced Audio Return Channel (eARC) on HDMI
- Advanced MCACC Auto Room Tuning
 - Auto Phase Control Plus
 - Subwoofer EQ
 - Multi-point Standing Wave Control
- > Advanced Sound Retriever (2ch)
- Advanced Surround Modes
 - Classical, Unplugged, Entertainment Show, Drama, Advanced Game, Action, Rock/Pop, Sports, Extended Stereo, Extended Mono, Front Stage Surround Advance

Video Features

- Ultra HD Pass-through with HDCP 2.2 (4K/60p/4:4:4/24-bit, 4K/24p/4:4:4/36-bit, 4K/60p/4:2:0/36-bit)*2
- > HDR10, HLG and BT.2020 Wide Color Gamut Signal Pass-through

- > Dolby Vision Compatible
- > Ultra HD Upscaling (1080p to 4K)
- > 3D Ready (Blu-ray Disc™, Broadcast, and Games)
- > Deep Color (36-bit), "x.v. Color"

Home Network Features

- ➤ FlareConnectTM for Multi-room Audio
- > Chromecast built-in*3 and Works with the Google Assistant
- > DTS Play-Fi with Pioneer Music Control App
- > Apple AirPlay 2
- > Works with SONOS
- Amazon Music, Pandora®, Spotify, TIDAL, and Deezer Hi-Fi Music-Streaming Services Ready*4
- > Internet Radio with TuneIn
- > Hi-Res Audio File Playback via USB/Network
 - $\bullet~$ Up to 192 kHz/24-bit ALAC*5, AIFF, FLAC, WAV (RIFF) and 11.2 MHz DSD*6

Convenience Features

- > Personal Preset
- > Dialog Enhancement
- > Dual Band (5 GHz/2.4 GHz) Wi-Fi® Built-in
- > Bluetooth® Wireless Technology (Version: 4.2 + LE, Profile: A2DP 1.2/ AVRCP 1.3, Codec: SBC/AAC) Built-in
- > Pioneer Remote App*7 Ready for Multi-room Entertainment Control and Network Streaming
- > User-Friendly GUI with System Setup Menu
- On-Screen Information for Audio/Video Status
- > PC Setup
- > Auto Power Off in HDMI Standby Through
- > AM/FM Tuner 40 Presets
- > Sleep Timer
- > User-Friendly Simple Remote Control

Front Terminals

- > HDMI 1 In
- > USB 1 In for USB Drive
- MCACC Setup MIC In
- > Phones 1 Out (Gold-Plated)

Rear Terminals

- > HDMI 6 In (4 Assignable)
- > HDMI 2 Out (1 for MAIN, 1 for SUB)
- > Ethernet 1 In
- > USB 1 In for USB Drive
- > AV (Component) 1 In (Assignable)

- > AV (Composite) 2 In (Assignable)
- > Audio 1 In (Assignable)
- > Phono (MM) 1 In
- > Digital Coaxial 1 In (Assignable)
- Digital Optical 1 In (Assignable)
- FRONT, CENTER, SURROUND, HEIGHT 1, SURROUND BACK, SUBWOOFER x 2 Pre Out
- > ZONE B Line Out for Wireless Headphones
- ZONE 2 Pre/Line Out, ZONE 3/HEIGHT 2 Pre/ Line Out
- Speaker 11ch Out (FRONT, CENTER, SURROUND, HEIGHT 1/Bi-AMP, SURROUND BACK/HEIGHT 2/ZONE 3, ZONE 2)
- > IR 1 In/1 Out

- > 12 V Trigger 2 Out
- > RS-232C
- > FM/AM Antenna

Specifications

- > Power Requirements: AC 120 V, 60 Hz
- > Power Consumption/Standby: 850 W/0.15 W
- Dimensions (W x H x D): 17-1/8 x 7-5/16 x 15-3/16 inches (435 x 185 x 386 mm)
- > Weight: 28.7 lbs. (13 kg)
- Carton Dimensions: 21-5/16 x 12-3/16 x 19-3/16 inches (541 x 310 x 487 mm)
- > Carton Included Weight: 35.3 lbs. (16.0 kg)
- *1 Available with future firmware update *2 Except AUX INPUT (Front) *3 Chromecast-enabled apps required *4 Service availability depends on country or region *5 Up to 96 kHz supported via wireless LAN *6 Converted to PCM. Not guaranteed via wireless LAN *7 Available for free download from the App Store/The Google Play



IMAX Enhanced*

The VSX-LX504 is IMAX Enhanced, certified to deliver the powerful sound just as intended by the filmmaker, and provide the immersive experience on your home theater.



* Function available with future firmware update

Dolby Atmos®/Dolby Surround Upmixing

By adding an external amplifier, the 9.2ch AV receiver can be expanded to decode 11ch to drive the 7.2.4ch configuration of Dolby Atmos®

DOLBY ATMOS

You can reproduce object-oriented sound in smooth, curving movements, or the realistic three-dimensional movement overhead by the top speakers. Other audio codecs such as PCM and DSD can be upmixed using Dolby Surround for enjoying 3D surround sound.

Dolby Atmos 7.2.4ch Speaker System



DTS:X®/DTS Neural:X Upmixing

DTS:X is the next-generation audio codec from DTS that leverages object-based audio to enable new immersive and interactive audio experiences. By adding an external



amplifier, the 9.2ch AV receiver can be expanded to decode 11ch for driving a 7.2.4ch surround system. Experience an immersive soundscape with incredibly rich and life-like audio. Other audio codecs such as PCM and DSD can be upmixed using DTS Neural:X for enjoying 3D surround sound.

DTS:X 7.2.4ch Speaker System



Dolby Atmos Height Virtualization*

When playing any Dolby format, engaging the Dolby Atmos Height Virtualizer enables a more immersive listening experience, creating a virtual surround and height effect from traditional speaker layouts without employing additional surround or height speakers

* Function available with future firmware update

Apple AirPlay 2

Apple AirPlay 2 lets you effortlessly stream music or podcasts to speakers throughout your house using any Apple device or by asking Siri, and it all stays in perfect sync.



Next Generation Video Standard Ready

The VSX-LX504 supports pass-through for HDR10, HLG (Hybrid Log-Gamma), and Dolby Vision signals. By connecting a compatible



DOLBY

source device, you can enjoy these latest video standards on a compatible display. What's more, all HDMI terminals support 4K (60p/4:4:4/24-bit), Wide Color Gamut (BT.2020), and HDCP 2.2, so you will have no problem when upgrading to new devices, and can also enjoy premium content such as 4K videos with digital copy protection.

HDR Dynamic Range Expansion Image





For illustration purpose only

Advanced MCACC Auto Room Tuning featuring Auto Phase Control Plus

Advanced MCACC adjusts the sound according to the listening room and speakers, and also creates clearer sound by suppressing the standing waves that occur between walls or ceiling and floor. Measurement of up to nine positions can be saved for a wide listening area. Auto Phase Control Plus* makes real-time analysis of the phase difference, and automatically compensates the gap between the LFE and main signals, providing strong bass and clear high-frequency sound.

* Effectiveness depends on content

Works with SONOS

By connecting the VSX-LX504 to Sonos Connect, you can play any music or audio source on your Sonos app. You can group the VSX-LX504 with other Sonos devices on the network, or use it independently. The AV receiver will automatically turn on and switch input as soon as you play music on your Sonos app.



Powered Zone 2/Zone 3

With the powered feature, the VSX-LX504 can directly drive speakers in other rooms, without the need for a separate amplifier. What's more, the dedicated DAC for Zone 2 lets you listen to all digital audio sources.





Zone B Output for Wireless Headphones

The VSX-LX504 is equipped with Zone B audio output terminals for expanding the Main Zone sound. You can listen to the sound playing in the living room via wireless headphones.



Chromecast built-in

The VSX-LX504 comes with Chromecast built-in, so you can use your mobile device to stream your favorite music, radio, or podcasts to your speaker. You can control the audio from anywhere in the house using Chromecastenabled apps running on your personal device-iPhone, iPad, Android phone and tablet, Mac and Windows laptop,





and Chromebook™. The VSX-LX504 also works with the Google Assistant, so you can tell it to turn up the volume, skip tracks, or stop the music using your Google Assistant enabled device, like Google Home. Discover Chromecastenabled apps at google.com/cast/apps.

Integrated Technologies





















































*PIONEER, MCACC, Phase Control, Advanced Sound Retriever, and the logos are registered trademarks of Pioneer Corporation, and are used under license. *The terms HDMI and HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing Administrator Inc. in the United States and other countries. *Dolby, Dolby Atmos, Dolby Surround, Dolby Vision, and the double-D symbol are registered trademarks of Dolby Laboratories. *Manufactured under license from IDTs, Inc. DTS, the Symbol, DTS and the Symbol of pathers, it is not provided to the Symbol of pathers, in the United States and/or other countries. *QIS, symbol, DTS and the Symbol of pather, it he DTS. Y, Play-Fi, the DTS. Y, Play-Fi, LLC. The Google Assistant requires an internet connection and is not available in certain languages or countries. Controlling certain devices in your home requires compatible smart devices. Subscriptions for services and applications may be required and additional terms, conditions and/or charges may apply